Tomasulo Example Cycle 0

Instruction status

Instruction		j	k	Issue	Execution complete	Write Result
LD	F6	34+	R2			
LD	F2	45+	R3			
MULTI	F0	F2	F4			
SUBD	F8	F6	F2			
DIVD	F10	F0	F6			
ADDD	F6	F8	F2			

	Busy	Address
Load1	No	
Load2	No	
Load3	No	

Reservation Stations

Time	Name	Busy	Op	S1 Vj	S2 Vk	RS for j Qj	RS for k Qk
0	Add1	No					
0	Add2	No					
	Add3	No					
0	Mult1	No					
0	Mult2	No					

Register result status

Clock	F0	F2	F4	F6	F8	F10	F12	...	F30
0	FU								

RHK.S96 7

Tomasulo Example Cycle 1

Instruction status

Instruction		j	k	Issue	Execution complete	Write Result
LD	F6	34+	R2	1		
LD	F2	45+	R3			
MULTI	F0	F2	F4			
SUBD	F8	F6	F2			
DIVD	F10	F0	F6			
ADDD	F6	F8	F2			

	Busy	Address
Load1	No	34+R2
Load2	No	
Load3	No	

Reservation Stations

Time	Name	Busy	Op	S1 Vj	S2 Vk	RS for j Qj	RS for k Qk
0	Add1	No					
0	Add2	No					
	Add3	No					
0	Mult1	No					
0	Mult2	No					

Register result status

Clock	F0	F2	F4	F6	F8	F10	F12	...	F30
1	FU			Load1					

RHK.S96 8

Tomasulo Example Cycle 2

Instruction status

Instruction	j	k	Issue	Execution complete	Write Result
LD F6	34+	R2	1		
LD F2	45+	R3	2		
MULTI F0	F2	F4			
SUBD F8	F6	F2			
DIVD F10	F0	F6			
ADDD F6	F8	F2			

	Busy	Address
Load1	Yes	34+R2
Load2	Yes	45+R3
Load3	No	

Reservation Stations

Time	Name	Busy	Op	S1 Vj	S2 Vk	RS for j Qj	RS for k Qk
0	Add1	No					
0	Add2	No					
	Add3	No					
0	Mult1	No					
0	Mult2	No					

Register result status

Clock	F0	F2	F4	F6	F8	F10	F12	...	F30
2	FU	Load2		Load1					

Tomasulo Example Cycle 3

Instruction status

Instruction	j	k	Issue	Execution complete	Write Result
LD F6	34+	R2	1	3	
LD F2	45+	R3	2		
MULTI F0	F2	F4	3		
SUBD F8	F6	F2			
DIVD F10	F0	F6			
ADDD F6	F8	F2			

	Busy	Address
Load1	Yes	34+R2
Load2	Yes	45+R3
Load3	No	

Reservation Stations

Time	Name	Busy	Op	S1 Vj	S2 Vk	RS for j Qj	RS for k Qk
0	Add1	No					
0	Add2	No					
	Add3	No					
0	Mult1	Yes	MULTD		R(F4)	Load2	
0	Mult2	No					

Register result status

Clock	F0	F2	F4	F6	F8	F10	F12	...	F30
3	FU	Mult1	Load2		Load1				

Tomasulo Example Cycle 4

Instruction status

Instruction		j	k	Issue	Execution complete	Write Result
LD	F6	34+	R2	1	3	4
LD	F2	45+	R3	2		
MULTI	F0	F2	F4	3		
SUBD	F8	F6	F2	4		
DIVD	F10	F0	F6			
ADDD	F6	F8	F2			

	Busy	Address
Load1	No	
Load2	Yes	45+R3
Load3	No	

Reservation Stations

Time	Name	Busy	Op	S1 Vj	S2 Vk	RS for j Qj	RS for k Qk
0	Add1	Yes	SUBD	M(34+R2)			Load2
0	Add2	No					
	Add3	No					
0	Mult1	Yes	MULTD		R(F4)	Load2	
0	Mult2	No					

Register result status

Clock		F0	F2	F4	F6	F8	F10	F12	...	F30
4	FU	Mult1	Load2		M(34+R2)	Add1				

Tomasulo Example Cycle 5

Instruction status

Instruction		j	k	Issue	Execution complete	Write Result
LD	F6	34+	R2	1	3	4
LD	F2	45+	R3	2	5	
MULTI	F0	F2	F4	3		
SUBD	F8	F6	F2	4		
DIVD	F10	F0	F6	5		
ADDD	F6	F8	F2			

	Busy	Address
Load1	No	
Load2	Yes	45+R3
Load3	No	

Reservation Stations

Time	Name	Busy	Op	S1 Vj	S2 Vk	RS for j Qj	RS for k Qk
0	Add1	Yes	SUBD	M(34+R2)			Load2
0	Add2	No					
	Add3	No					
0	Mult1	Yes	MULTD		R(F4)	Load2	
0	Mult2	Yes	DIVD		M(34+R2)	Mult1	

Register result status

Clock		F0	F2	F4	F6	F8	F10	F12	...	F30
5	FU	Mult1	Load2		M(34+R2)	Add1	Mult2			

Tomasulo Example Cycle 6

Instruction status

Instruction		j	k	Issue	Execution complete	Write Result
LD	F6	34+	R2	1	3	4
LD	F2	45+	R3	2	5	6
MULTI	F0	F2	F4	3		
SUBD	F8	F6	F2	4		
DIVD	F10	F0	F6	5		
ADDD	F6	F8	F2	6		

	Busy	Address
Load1	No	
Load2	No	
Load3	No	

Reservation Stations

Time	Name	Busy	Op	S1 Vj	S2 Vk	RS for j Qj	RS for k Qk
2	Add1	Yes	SUBD	M(34+R2)	M(45+R3)		
0	Add2	Yes	ADDD		M(45+R3)	Add1	
	Add3	No					
10	Mult1	Yes	MULTD	M(45+R3)	R(F4)		
0	Mult2	Yes	DIVD		M(34+R2)	Mult1	

Register result status

Clock		F0	F2	F4	F6	F8	F10	F12	...	F30
6	FU	Mult1	M(45+R3)		Add2	Add1	Mult2			

Tomasulo Example Cycle 7

Instruction status

Instruction		j	k	Issue	Execution complete	Write Result
LD	F6	34+	R2	1	3	4
LD	F2	45+	R3	2	5	6
MULTI	F0	F2	F4	3		
SUBD	F8	F6	F2	4		
DIVD	F10	F0	F6	5		
ADDD	F6	F8	F2	6		

	Busy	Address
Load1	No	
Load2	No	
Load3	No	

Reservation Stations

Time	Name	Busy	Op	S1 Vj	S2 Vk	RS for j Qj	RS for k Qk
1	Add1	Yes	SUBD	M(34+R2)	M(45+R3)		
0	Add2	Yes	ADDD		M(45+R3)	Add1	
	Add3	No					
9	Mult1	Yes	MULTD	M(45+R3)	R(F4)		
0	Mult2	Yes	DIVD		M(34+R2)	Mult1	

Register result status

Clock		F0	F2	F4	F6	F8	F10	F12	...	F30
7	FU	Mult1	M(45+R3)		Add2	Add1	Mult2			

Tomasulo Example Cycle 8

Instruction status

Instruction	j	k	Issue	Execution complete	Write Result
LD F6	34+	R2	1	3	4
LD F2	45+	R3	2	5	6
MULTI F0	F2	F4	3		
SUBD F8	F6	F2	4	8	
DIVD F10	F0	F6	5		
ADDD F6	F8	F2	6		

	Busy	Address
Load1	No	
Load2	No	
Load3	No	

Reservation Stations

Time	Name	Busy	Op	S1 Vj	S2 Vk	RS for j Qj	RS for k Qk
0	Add1	Yes	SUBD	M(34+R2)	M(45+R3)		
0	Add2	Yes	ADDD		M(45+R3)	Add1	
	Add3	No					
8	Mult1	Yes	MULTD	M(45+R3)	R(F4)		
0	Mult2	Yes	DIVD		M(34+R2)	Mult1	

Register result status

Clock		F0	F2	F4	F6	F8	F10	F12	...	F30
8	FU	Mult1	M(45+R3)		Add2	Add1	Mult2			

Tomasulo Example Cycle 9

Instruction status

Instruction	j	k	Issue	Execution complete	Write Result
LD F6	34+	R2	1	3	4
LD F2	45+	R3	2	5	6
MULTI F0	F2	F4	3		
SUBD F8	F6	F2	4	8	9
DIVD F10	F0	F6	5		
ADDD F6	F8	F2	6		

	Busy	Address
Load1	No	
Load2	No	
Load3	No	

Reservation Stations

Time	Name	Busy	Op	S1 Vj	S2 Vk	RS for j Qj	RS for k Qk
0	Add1	No					
0	Add2	Yes	ADDD	M()–M()	M(45+R3)		
	Add3	No					
7	Mult1	Yes	MULTD	M(45+R3)	R(F4)		
0	Mult2	Yes	DIVD		M(34+R2)	Mult1	

Register result status

Clock		F0	F2	F4	F6	F8	F10	F12	...	F30
9	FU	Mult1	M(45+R3)		Add2	M()–M()	Mult2			

Tomasulo Example Cycle 10

Instruction status

Instruction		j	k	Issue	Execution complete	Write Result
LD	F6	34+	R2	1	3	4
LD	F2	45+	R3	2	5	6
MULTI	F0	F2	F4	3		
SUBD	F8	F6	F2	4	8	9
DIVD	F10	F0	F6	5		
ADDD	F6	F8	F2	6		

	Busy	Address
Load1	No	
Load2	No	
Load3	No	

Reservation Stations

Time	Name	Busy	Op	S1 Vj	S2 Vk	RS for j Qj	RS for k Qk
0	Add1	No					
2	Add2	Yes	ADDD	M()–M()	M(45+R3)		
	Add3	No					
7	Mult1	Yes	MULTD	M(45+R3)	R(F4)		
0	Mult2	Yes	DIVD		M(34+R2)	Mult1	

Register result status

Clock		F0	F2	F4	F6	F8	F10	F12	...	F30
10	FU	Mult1	M(45+R3)		Add2	M()–M()	Mult2			

Tomasulo Example Cycle 11

Instruction status

Instruction		j	k	Issue	Execution complete	Write Result
LD	F6	34+	R2	1	3	4
LD	F2	45+	R3	2	5	6
MULTI	F0	F2	F4	3		
SUBD	F8	F6	F2	4	8	9
DIVD	F10	F0	F6	5		
ADDD	F6	F8	F2	6		

	Busy	Address
Load1	No	
Load2	No	
Load3	No	

Reservation Stations

Time	Name	Busy	Op	S1 Vj	S2 Vk	RS for j Qj	RS for k Qk
0	Add1	No					
1	Add2	Yes	ADDD	M()–M()	M(45+R3)		
	Add3	No					
5	Mult1	Yes	MULTD	M(45+R3)	R(F4)		
0	Mult2	Yes	DIVD		M(34+R2)	Mult1	

Register result status

Clock		F0	F2	F4	F6	F8	F10	F12	...	F30
11	FU	Mult1	M(45+R3)		Add2	M()–M()	Mult2			

Tomasulo Example Cycle 12

Instruction status

Instruction	j	k	Issue	Execution complete	Write Result
LD F6	34+	R2	1	3	4
LD F2	45+	R3	2	5	6
MULTI F0	F2	F4	3		
SUBD F8	F6	F2	4	8	9
DIVD F10	F0	F6	5		
ADDD F6	F8	F2	6	12	

	Busy	Address
Load1	No	
Load2	No	
Load3	No	

Reservation Stations

Time	Name	Busy	Op	S1 Vj	S2 Vk	RS for j Qj	RS for k Qk
0	Add1	No					
0	Add2	Yes	ADDD	M()–M()	M(45+R3)		
	Add3	No					
4	Mult1	Yes	MULTD	M(45+R3)	R(F4)		
0	Mult2	Yes	DIVD		M(34+R2)	Mult1	

Register result status

Clock	F0	F2	F4	F6	F8	F10	F12	...	F30
12	FU	Mult1	M(45+R3)		Add2	M()–M()	Mult2		

Tomasulo Example Cycle 13

Instruction status

Instruction	j	k	Issue	Execution complete	Write Result
LD F6	34+	R2	1	3	4
LD F2	45+	R3	2	5	6
MULTI F0	F2	F4	3		
SUBD F8	F6	F2	4	8	9
DIVD F10	F0	F6	5		
ADDD F6	F8	F2	6	12	13

	Busy	Address
Load1	No	
Load2	No	
Load3	No	

Reservation Stations

Time	Name	Busy	Op	S1 Vj	S2 Vk	RS for j Qj	RS for k Qk
0	Add1	No					
0	Add2	No					
	Add3	No					
3	Mult1	Yes	MULTD	M(45+R3)	R(F4)		
0	Mult2	Yes	DIVD		M(34+R2)	Mult1	

Register result status

Clock	F0	F2	F4	F6	F8	F10	F12	...	F30
13	FU	Mult1	M(45+R3)		(M–M)+M()	M()–M()	Mult2		

Tomasulo Example Cycle 14

Instruction status

Instruction		j	k	Issue	Execution complete	Write Result
LD	F6	34+	R2	1	3	4
LD	F2	45+	R3	2	5	6
MULTI	F0	F2	F4	3		
SUBD	F8	F6	F2	4	8	9
DIVD	F10	F0	F6	5		
ADDD	F6	F8	F2	6	12	13

	Busy	Address
Load1	No	
Load2	No	
Load3	No	

Reservation Stations

Time	Name	Busy	Op	S1 Vj	S2 Vk	RS for j Qj	RS for k Qk
0	Add1	No					
0	Add2	No					
	Add3	No					
2	Mult1	Yes	MULTD	M(45+R3)	R(F4)		
0	Mult2	Yes	DIVD		M(34+R2)	Mult1	

Register result status

Clock		F0	F2	F4	F6	F8	F10	F12	...	F30
14	FU	Mult1	M(45+R3)		(M–M)+M()	M()–M()	Mult2			

Tomasulo Example Cycle 15

Instruction status

Instruction		j	k	Issue	Execution complete	Write Result
LD	F6	34+	R2	1	3	4
LD	F2	45+	R3	2	5	6
MULTI	F0	F2	F4	3		
SUBD	F8	F6	F2	4	8	9
DIVD	F10	F0	F6	5		
ADDD	F6	F8	F2	6	12	13

	Busy	Address
Load1	No	
Load2	No	
Load3	No	

Reservation Stations

Time	Name	Busy	Op	S1 Vj	S2 Vk	RS for j Qj	RS for k Qk
0	Add1	No					
0	Add2	No					
	Add3	No					
1	Mult1	Yes	MULTD	M(45+R3)	R(F4)		
0	Mult2	Yes	DIVD		M(34+R2)	Mult1	

Register result status

Clock		F0	F2	F4	F6	F8	F10	F12	...	F30
15	FU	Mult1	M(45+R3)		(M–M)+M()	M()–M()	Mult2			

Tomasulo Example Cycle 16

Instruction status

Instruction		j	k	Issue	Execution complete	Write Result
LD	F6	34+	R2	1	3	4
LD	F2	45+	R3	2	5	6
MULTI	F0	F2	F4	3	16	
SUBD	F8	F6	F2	4	8	9
DIVD	F10	F0	F6	5		
ADDD	F6	F8	F2	6	12	13

	Busy	Address
Load1	No	
Load2	No	
Load3	No	

Reservation Stations

Time	Name	Busy	Op	S1 Vj	S2 Vk	RS for j Qj	RS for k Qk
0	Add1	No					
0	Add2	No					
	Add3	No					
0	Mult1	Yes	MULTD	M(45+R3)	R(F4)		
0	Mult2	Yes	DIVD		M(34+R2)	Mult1	

Register result status

Clock		F0	F2	F4	F6	F8	F10	F12	...	F30
16	FU	Mult1	M(45+R3)		(M–M)+M()	M()–M()	Mult2			

Tomasulo Example Cycle 17

Instruction status

Instruction		j	k	Issue	Execution complete	Write Result
LD	F6	34+	R2	1	3	4
LD	F2	45+	R3	2	5	6
MULTI	F0	F2	F4	3	16	17
SUBD	F8	F6	F2	4	8	9
DIVD	F10	F0	F6	5		
ADDD	F6	F8	F2	6	12	13

	Busy	Address
Load1	No	
Load2	No	
Load3	No	

Reservation Stations

Time	Name	Busy	Op	S1 Vj	S2 Vk	RS for j Qj	RS for k Qk
0	Add1	No					
0	Add2	No					
	Add3	No					
0	Mult1	No					
0	Mult2	Yes	DIVD	M*F4	M(34+R2)		

Register result status

Clock		F0	F2	F4	F6	F8	F10	F12	...	F30
17	FU	M*F4	M(45+R3)		(M–M)+M()	M()–M()	Mult2			

Tomasulo Example Cycle 18

Instruction status

Instruction	j	k	Issue	Execution complete	Write Result
LD F6	34+	R2	1	3	4
LD F2	45+	R3	2	5	6
MULTI F0	F2	F4	3	16	17
SUBD F8	F6	F2	4	8	9
DIVD F10	F0	F6	5		
ADDD F6	F8	F2	6	12	13

	Busy	Address
Load1	No	
Load2	No	
Load3	No	

Reservation Stations

Time	Name	Busy	Op	S1 Vj	S2 Vk	RS for j Qj	RS for k Qk
0	Add1	No					
0	Add2	No					
	Add3	No					
0	Mult1	No					
40	Mult2	Yes	DIVD	M*F4	M(34+R2)		

Register result status

Clock	F0	F2	F4	F6	F8	F10	F12 ...	F30
18	FU	M*F4	M(45+R3)		(M–M)+M()	M()–M()	Mult2	

Tomasulo Example Cycle 57

Instruction status

Instruction	j	k	Issue	Execution complete	Write Result
LD F6	34+	R2	1	3	4
LD F2	45+	R3	2	5	6
MULTI F0	F2	F4	3	16	17
SUBD F8	F6	F2	4	8	9
DIVD F10	F0	F6	5		
ADDD F6	F8	F2	6	12	13

	Busy	Address
Load1	No	
Load2	No	
Load3	No	

Reservation Stations

Time	Name	Busy	Op	S1 Vj	S2 Vk	RS for j Qj	RS for k Qk
0	Add1	No					
0	Add2	No					
	Add3	No					
0	Mult1	No					
1	Mult2	Yes	DIVD	M*F4	M(34+R2)		

Register result status

Clock	F0	F2	F4	F6	F8	F10	F12 ...	F30
57	FU	M*F4	M(45+R3)		(M–M)+M()	M()–M()	Mult2	

Tomasulo Example Cycle 58

Instruction status

Instruction	j	k	Issue	Execution complete	Write Result
LD F6	34+	R2	1	3	4
LD F2	45+	R3	2	5	6
MULTI F0	F2	F4	3	16	17
SUBD F8	F6	F2	4	8	9
DIVD F10	F0	F6	5	58	
ADDD F6	F8	F2	6	12	13

	Busy	Address
Load1	No	
Load2	No	
Load3	No	

Reservation Stations

Time	Name	Busy	Op	S1 Vj	S2 Vk	RS for j Qj	RS for k Qk
0	Add1	No					
0	Add2	No					
	Add3	No					
0	Mult1	No					
0	Mult2	Yes	DIVD	M*F4	M(34+R2)		

Register result status

Clock	F0	F2	F4	F6	F8	F10	F12	...	F30
58	FU	M*F4	M(45+R3)		(M–M)+M()	M()–M()	Mult2		

Tomasulo Example Cycle 59

Instruction status

Instruction	j	k	Issue	Execution complete	Write Result
LD F6	34+	R2	1	3	4
LD F2	45+	R3	2	5	6
MULTI F0	F2	F4	3	16	17
SUBD F8	F6	F2	4	8	9
DIVD F10	F0	F6	5	58	59
ADDD F6	F8	F2	6	12	13

	Busy	Address
Load1	No	
Load2	No	
Load3	No	

Reservation Stations

Time	Name	Busy	Op	S1 Vj	S2 Vk	RS for j Qj	RS for k Qk
0	Add1	No					
0	Add2	No					
	Add3	No					
0	Mult1	No					
0	Mult2	No					

Register result status

Clock	F0	F2	F4	F6	F8	F10	F12	...	F30
59	FU	M*F4	M(45+R3)		(M–M)+M()	M()–M()	M*F4/M		

Tomasulo Loop Example

```
Loop: LD      F0   0    R1
      MULTD   F4   F0   F2
      SD      F4   0    R1
      SUBI    R1   R1   #8
      BNEZ    R1   Loop
```

- **Multiply takes 4 clocks**
- **Load have cache misses**

Loop Example Cycle 0

Instruction status

Instruction	j	k	iteration	Issue	Execution complete	Write Result
LD F0	0	R1	1			
MULTI F4	F0	F2	1			
SD F4	0	R1	1			
LD F0	0	R1	2			
MULTI F4	F0	F2	2			
SD F4	0	R1	2			

	Busy	Address	Qi
Load1	No		
Load2	No		
Load3	No		
Store1	No		
Store2	No		
Store3	No		

Reservation Stations

Time	Name	Busy	Op	S1 Vj	S2 Vk	RS for Qj	RS for Qk
0	Add1	No					
0	Add2	No					
0	Add3	No					
0	Mult1	No					
0	Mult2	No					

Code:

```
LD    F0   0  R1
MULTI F4   F0 F2
SD    F4   0  R1
SUBI  R1   R1 # 8
BNEZ  R1   Loop
```

Register result status

Clock	R1	F0	F2	F4	F6	F8	F10	F12 ...	F30
0	80	Qi							

Loop Example Cycle 1

Instruction status

Instruction	j	k	iteration	Issue	Execution complete	Write Result
LD F0	0	R1	1	1		
MULTI F4	F0	F2	1			
SD F4	0	R1	1			
LD F0	0	R1	2			
MULTI F4	F0	F2	2			
SD F4	0	R1	2			

	Busy	Address	Qi
Load1	Yes	80	
Load2	No		
Load3	No		
Store1	No		
Store2	No		
Store3	No		

Reservation Stations

Time	Name	Busy	Op	S1 Vj	S2 Vk	RS for Qj	RS for Qk	Code:
0	Add1	No						LD F0 0 R1
0	Add2	No						MULTI F4 F0 F2
0	Add3	No						SD F4 0 R1
0	Mult1	No						SUBI R1 R1 #8
0	Mult2	No						BNEZ R1 Loop

Register result status

Clock	R1		F0	F2	F4	F6	F8	F10	F12 ...	F30
1	80	Qi	Load1							

Loop Example Cycle 2

Instruction status

Instruction	j	k	iteration	Issue	Execution complete	Write Result
LD F0	0	R1	1	1		
MULTI F4	F0	F2	1	2		
SD F4	0	R1	1			
LD F0	0	R1	2			
MULTI F4	F0	F2	2			
SD F4	0	R1	2			

	Busy	Address	Qi
Load1	Yes	80	
Load2	No		
Load3	No		
Store1	No		
Store2	No		
Store3	No		

Reservation Stations

Time	Name	Busy	Op	S1 Vj	S2 Vk	RS for Qj	RS for Qk	Code:
0	Add1	No						LD F0 0 R1
0	Add2	No						MULTI F4 F0 F2
0	Add3	No						SD F4 0 R1
0	Mult1	Yes	MULTD		R(F2)	Load1		SUBI R1 R1 #8
0	Mult2	No						BNEZ R1 Loop

Register result status

Clock	R1		F0	F2	F4	F6	F8	F10	F12 ...	F30
2	80	Qi	Load1		Mult1					

Loop Example Cycle 3

Instruction status

Instruction	j	k	iteration	Issue	Execution complete	Write Result
LD F0	0	R1	1	1		
MULTI F4	F0	F2	1	2		
SD F4	0	R1	1	3		
LD F0	0	R1	2			
MULTI F4	F0	F2	2			
SD F4	0	R1	2			

	Busy	Address	Qi
Load1	Yes	80	
Load2	No		
Load3	No		
Store1	Yes	80	Mult1
Store2	No		
Store3	No		

Reservation Stations

Time	Name	Busy	Op	S1 Vj	S2 Vk	RS for Qj	RS for Qk
0	Add1	No					
0	Add2	No					
0	Add3	No					
0	Mult1	Yes	MULTD		R(F2)	Load1	
0	Mult2	No					

Code:

```
LD   F0   0 R1
MULTI F4  F0 F2
SD   F4   0 R1
SUBI R1   R1 #8
BNEZ R1   Loop
```

Register result status

Clock	R1		F0	F2	F4	F6	F8	F10	F12 ...	F30
3	80	Qi	Load1		Mult1					

Loop Example Cycle 4

Instruction status

Instruction	j	k	iteration	Issue	Execution complete	Write Result
LD F0	0	R1	1	1		
MULTI F4	F0	F2	1	2		
SD F4	0	R1	1	3		
LD F0	0	R1	2			
MULTI F4	F0	F2	2			
SD F4	0	R1	2			

	Busy	Address	Qi
Load1	Yes	80	
Load2	No		
Load3	No		
Store1	Yes	80	Mult1
Store2	No		
Store3	No		

Reservation Stations

Time	Name	Busy	Op	S1 Vj	S2 Vk	RS for Qj	RS for Qk
0	Add1	No					
0	Add2	No					
0	Add3	No					
0	Mult1	Yes	MULTD		R(F2)	Load1	
0	Mult2	No					

Code:

```
LD   F0   0 R1
MULTI F4  F0 F2
SD   F4   0 R1
SUBI R1   R1 #8
BNEZ R1   Loop
```

Register result status

Clock	R1		F0	F2	F4	F6	F8	F10	F12 ...	F30
4	72	Qi	Load1		Mult1					

Loop Example Cycle 5

Instruction status

Instruction	j	k	iteration	Issue	Execution complete	Write Result
LD F0	0	R1	1	1		
MULTI F4	F0	F2	1	2		
SD F4	0	R1	1	3		
LD F0	0	R1	2			
MULTI F4	F0	F2	2			
SD F4	0	R1	2			

	Busy	Address	Qi
Load1	Yes	80	
Load2	No		
Load3	No		
Store1	Yes	80	Mult1
Store2	No		
Store3	No		

Reservation Stations

Time	Name	Busy	Op	S1 Vj	S2 Vk	RS for Qj	RS for Qk	Code:
0	Add1	No						LD F0 0 R1
0	Add2	No						MULTI F4 F0 F2
0	Add3	No						SD F4 0 R1
0	Mult1	Yes	MULTD		R(F2)	Load1		SUBI R1 R1 # 8
0	Mult2	No						BNEZ R1 Loop

Register result status

Clock	R1		F0	F2	F4	F6	F8	F10	F12 ...	F30
5	72	Qi	Load1		Mult1					

Loop Example Cycle 6

Instruction status

Instruction	j	k	iteration	Issue	Execution complete	Write Result
LD F0	0	R1	1	1		
MULTI F4	F0	F2	1	2		
SD F4	0	R1	1	3		
LD F0	0	R1	2	6		
MULTI F4	F0	F2	2			
SD F4	0	R1	2			

	Busy	Address	Qi
Load1	Yes	80	
Load2	Yes	72	
Load3	No		
Store1	Yes	80	Mult1
Store2	No		
Store3	No		

Reservation Stations

Time	Name	Busy	Op	S1 Vj	S2 Vk	RS for Qj	RS for Qk	Code:
0	Add1	No						LD F0 0 R1
0	Add2	No						MULTI F4 F0 F2
0	Add3	No						SD F4 0 R1
0	Mult1	Yes	MULTD		R(F2)	Load1		SUBI R1 R1 # 8
0	Mult2	No						BNEZ R1 Loop

Register result status

Clock	R1		F0	F2	F4	F6	F8	F10	F12 ...	F30
6	72	Qi	Load1		Mult1					

Loop Example Cycle 7

Instruction status

Instruction	j	k	iteration	Issue	Execution complete	Write Result
LD F0	0	R1	1	1		
MULTI F4	F0	F2	1	2		
SD F4	0	R1	1	3		
LD F0	0	R1	2	6		
MULTI F4	F0	F2	2	7		
SD F4	0	R1	2			

	Busy	Address	Qi
Load1	Yes	80	
Load2	Yes	72	
Load3	No		
Store1	Yes	80	Mult1
Store2	No		
Store3	No		

Reservation Stations

Time	Name	Busy	Op	S1 Vj	S2 Vk	RS for Qj	RS for Qk
0	Add1	No					
0	Add2	No					
0	Add3	No					
0	Mult1	Yes	MULTD		R(F2)	Load1	
0	Mult2	Yes	MULTD		R(F2)	Load2	

Code:

```
LD   F0   0 R1
MULTI F4  F0 F2
SD   F4   0 R1
SUBI R1   R1 #8
BNEZ R1   Loop
```

Register result status

Clock	R1		F0	F2	F4	F6	F8	F10	F12 ...	F30
7	72	Qi	Load2		Mult2					

Loop Example Cycle 8

Instruction status

Instruction	j	k	iteration	Issue	Execution complete	Write Result
LD F0	0	R1	1	1		
MULTI F4	F0	F2	1	2		
SD F4	0	R1	1	3		
LD F0	0	R1	2	6		
MULTI F4	F0	F2	2	7		
SD F4	0	R1	2	8		

	Busy	Address	Qi
Load1	Yes	80	
Load2	Yes	72	
Load3	No		
Store1	Yes	80	Mult1
Store2	Yes	72	Mult2
Store3	No		

Reservation Stations

Time	Name	Busy	Op	S1 Vj	S2 Vk	RS for Qj	RS for Qk
0	Add1	No					
0	Add2	No					
0	Add3	No					
0	Mult1	Yes	MULTD		R(F2)	Load1	
0	Mult2	Yes	MULTD		R(F2)	Load2	

Code:

```
LD   F0   0 R1
MULTI F4  F0 F2
SD   F4   0 R1
SUBI R1   R1 #8
BNEZ R1   Loop
```

Register result status

Clock	R1		F0	F2	F4	F6	F8	F10	F12 ...	F30
8	72	Qi	Load2		Mult2					

Loop Example Cycle 9

Instruction status

Instruction	j	k	iteration	Issue	Execution complete	Write Result
LD F0	0	R1	1	1	9	
MULTI F4	F0	F2	1	2		
SD F4	0	R1	1	3		
LD F0	0	R1	2	6		
MULTI F4	F0	F2	2	7		
SD F4	0	R1	2	8		

	Busy	Address	Qi
Load1	Yes	80	
Load2	Yes	72	
Load3	No		
Store1	Yes	80	Mult1
Store2	Yes	72	Mult2
Store3	No		

Reservation Stations

Time	Name	Busy	Op	S1 Vj	S2 Vk	RS for Qj	RS for Qk	Code:
0	Add1	No						LD F0 0 R1
0	Add2	No						MULTI F4 F0 F2
0	Add3	No						SD F4 0 R1
0	Mult1	Yes	MULTD		R(F2)	Load1		SUBI R1 R1 # 8
0	Mult2	Yes	MULTD		R(F2)	Load2		BNEZ R1 Loop

Register result status

Clock	R1		F0	F2	F4	F6	F8	F10	F12 ...	F30
9	64	Qi	Load2		Mult2					

Loop Example Cycle 10

Instruction status

Instruction	j	k	iteration	Issue	Execution complete	Write Result
LD F0	0	R1	1	1	9	10
MULTI F4	F0	F2	1	2		
SD F4	0	R1	1	3		
LD F0	0	R1	2	6	10	
MULTI F4	F0	F2	2	7		
SD F4	0	R1	2	8		

	Busy	Address	Qi
Load1	No		
Load2	Yes	72	
Load3	No		
Store1	Yes	80	Mult1
Store2	Yes	72	Mult2
Store3	No		

Reservation Stations

Time	Name	Busy	Op	S1 Vj	S2 Vk	RS for Qj	RS for Qk	Code:
0	Add1	No						LD F0 0 R1
0	Add2	No						MULTI F4 F0 F2
0	Add3	No						SD F4 0 R1
4	Mult1	Yes	MULTD	M(80)	R(F2)			SUBI R1 R1 # 8
0	Mult2	Yes	MULTD		R(F2)	Load2		BNEZ R1 Loop

Register result status

Clock	R1		F0	F2	F4	F6	F8	F10	F12 ...	F30
10	64	Qi	Load2		Mult2					

Loop Example Cycle 11

Instruction status

Instruction	j	k	iteration	Issue	Execution complete	Write Result
LD F0	0	R1	1	1	9	10
MULTI F4	F0	F2	1	2		
SD F4	0	R1	1	3		
LD F0	0	R1	2	6	10	11
MULTI F4	F0	F2	2	7		
SD F4	0	R1	2	8		

	Busy	Address	Qi
Load1	No		
Load2	No		
Load3	Yes	64	Qi
Store1	Yes	80	Mult1
Store2	Yes	72	Mult2
Store3	No		

Reservation Stations

Time	Name	Busy	Op	S1 Vj	S2 Vk	RS for Qj	RS for Qk	Code:
0	Add1	No						LD F0 0 R1
0	Add2	No						MULTI F4 F0 F2
0	Add3	No						SD F4 0 R1
3	Mult1	Yes	MULTD	M(80)	R(F2)			SUBI R1 R1 # 8
4	Mult2	Yes	MULTD	M(72)	R(F2)			BNEZ R1 Loop

Register result status

Clock	R1		F0	F2	F4	F6	F8	F10	F12 ...	F30
11	64	Qi			Mult2					

Loop Example Cycle 12

Instruction status

Instruction	j	k	iteration	Issue	Execution complete	Write Result
LD F0	0	R1	1	1	9	10
MULTI F4	F0	F2	1	2		
SD F4	0	R1	1	3		
LD F0	0	R1	2	6	10	11
MULTI F4	F0	F2	2	7		
SD F4	0	R1	2	8		

	Busy	Address	Qi
Load1	No		
Load2	No		
Load3	Yes	64	Qi
Store1	Yes	80	Mult1
Store2	Yes	72	Mult2
Store3	No		

Reservation Stations

Time	Name	Busy	Op	S1 Vj	S2 Vk	RS for Qj	RS for Qk	Code:
0	Add1	No						LD F0 0 R1
0	Add2	No						MULTI F4 F0 F2
0	Add3	No						SD F4 0 R1
2	Mult1	Yes	MULTD	M(80)	R(F2)			SUBI R1 R1 # 8
3	Mult2	Yes	MULTD	M(72)	R(F2)			BNEZ R1 Loop

Register result status

Clock	R1		F0	F2	F4	F6	F8	F10	F12 ...	F30
12	64	Qi			Mult2					

Loop Example Cycle 13

Instruction status

Instruction	j	k	iteration	Issue	Execution complete	Write Result
LD F0	0	R1	1	1	9	10
MULTI F4	F0	F2	1	2		
SD F4	0	R1	1	3		
LD F0	0	R1	2	6	10	11
MULTI F4	F0	F2	2	7		
SD F4	0	R1	2	8		

	Busy	Address	Qi
Load1	No		
Load2	No		
Load3	Yes	64	
Store1	Yes	80	Mult1
Store2	Yes	72	Mult2
Store3	No		

Reservation Stations

Time	Name	Busy	Op	S1 Vj	S2 Vk	RS for Qj	RS for Qk	Code:
0	Add1	No						LD F0 0 R1
0	Add2	No						MULTI F4 F0 F2
0	Add3	No						SD F4 0 R1
1	Mult1	Yes	MULTD	M(80)	R(F2)			SUBI R1 R1 # 8
2	Mult2	Yes	MULTD	M(72)	R(F2)			BNEZ R1 Loop

Register result status

Clock	R1		F0	F2	F4	F6	F8	F10	F12 ...	F30
13	64	Qi			Mult2					

Loop Example Cycle 14

Instruction status

Instruction	j	k	iteration	Issue	Execution complete	Write Result
LD F0	0	R1	1	1	9	10
MULTI F4	F0	F2	1	2	14	
SD F4	0	R1	1	3		
LD F0	0	R1	2	6	10	11
MULTI F4	F0	F2	2	7		
SD F4	0	R1	2	8		

	Busy	Address	Qi
Load1	No		
Load2	No		
Load3	Yes	64	
Store1	Yes	80	Mult1
Store2	Yes	72	Mult2
Store3	No		

Reservation Stations

Time	Name	Busy	Op	S1 Vj	S2 Vk	RS for Qj	RS for Qk	Code:
0	Add1	No						LD F0 0 R1
0	Add2	No						MULTI F4 F0 F2
0	Add3	No						SD F4 0 R1
0	Mult1	Yes	MULTD	M(80)	R(F2)			SUBI R1 R1 # 8
1	Mult2	Yes	MULTD	M(72)	R(F2)			BNEZ R1 Loop

Register result status

Clock	R1		F0	F2	F4	F6	F8	F10	F12 ...	F30
14	64	Qi			Mult2					

Loop Example Cycle 15

Instruction status

Instruction	j	k	iteration	Issue	Execution complete	Write Result
LD F0	0	R1	1	1	9	10
MULTI F4	F0	F2	1	2	14	15
SD F4	0	R1	1	3		
LD F0	0	R1	2	6	10	11
MULTI F4	F0	F2	2	7	15	
SD F4	0	R1	2	8		

	Busy	Address	Qi
Load1	No		
Load2	No		
Load3	Yes	64	
Store1	Yes	80	M(80)*R(
Store2	Yes	72	Mult2
Store3	No		

Reservation Stations

Time	Name	Busy	Op	S1 Vj	S2 Vk	RS for Qj	RS for Qk
0	Add1	No					
0	Add2	No					
0	Add3	No					
0	Mult1	No					
0	Mult2	Yes	MULTD	M(72)	R(F2)		

Code:

```
LD   F0   0 R1
MULTI F4  F0 F2
SD   F4   0 R1
SUBI R1   R1 #8
BNEZ R1   Loop
```

Register result status

Clock	R1		F0	F2	F4	F6	F8	F10	F12 ...	F30
15	64	Qi			Mult2					

Loop Example Cycle 16

Instruction status

Instruction	j	k	iteration	Issue	Execution complete	Write Result
LD F0	0	R1	1	1	9	10
MULTI F4	F0	F2	1	2	14	15
SD F4	0	R1	1	3		
LD F0	0	R1	2	6	10	11
MULTI F4	F0	F2	2	7	15	16
SD F4	0	R1	2	8		

	Busy	Address	Qi
Load1	No		
Load2	No		
Load3	Yes	64	
Store1	Yes	80	M(80)*R(
Store2	Yes	72	M(72)*R(
Store3	No		

Reservation Stations

Time	Name	Busy	Op	S1 Vj	S2 Vk	RS for Qj	RS for Qk
0	Add1	No					
0	Add2	No					
0	Add3	No					
0	Mult1	Yes	MULTD		R(F2)	Load3	
0	Mult2	No					

Code:

```
LD   F0   0 R1
MULTI F4  F0 F2
SD   F4   0 R1
SUBI R1   R1 #8
BNEZ R1   Loop
```

Register result status

Clock	R1		F0	F2	F4	F6	F8	F10	F12 ...	F30
16	64	Qi			Mult1					

Loop Example Cycle 17

Instruction status

Instruction	j	k	iteration	Issue	Execution complete	Write Result
LD F0	0	R1	1	1	9	10
MULTI F4	F0	F2	1	2	14	15
SD F4	0	R1	1	3		
LD F0	0	R1	2	6	10	11
MULTI F4	F0	F2	2	7	15	16
SD F4	0	R1	2	8		

	Busy	Address	Qi
Load1	No		
Load2	No		
Load3	Yes	64	
Store1	Yes	80	M(80)*R(
Store2	Yes	72	M(72)*R(
Store3	Yes	64	Mult1

Reservation Stations

Time	Name	Busy	Op	S1 Vj	S2 Vk	RS for Qj	RS for Qk	Code:			
0	Add1	No						LD	F0	0	R1
0	Add2	No						MULTI	F4	F0	F2
0	Add3	No						SD	F4	0	R1
0	Mult1	Yes	MULTD		R(F2)	Load3		SUBI	R1	R1	#8
0	Mult2	No						BNEZ	R1	Loop	

Register result status

Clock	R1		F0	F2	F4	F6	F8	F10	F12	...	F30
17	64	Qi			Mult1						

Loop Example Cycle 18

Instruction status

Instruction	j	k	iteration	Issue	Execution complete	Write Result
LD F0	0	R1	1	1	9	10
MULTI F4	F0	F2	1	2	14	15
SD F4	0	R1	1	3	18	
LD F0	0	R1	2	6	10	11
MULTI F4	F0	F2	2	7	15	16
SD F4	0	R1	2	8		

	Busy	Address	Qi
Load1	No		
Load2	No		
Load3	Yes	64	
Store1	Yes	80	M(80)*R(
Store2	Yes	72	M(72)*R(
Store3	Yes	64	Mult1

Reservation Stations

Time	Name	Busy	Op	S1 Vj	S2 Vk	RS for Qj	RS for Qk	Code:			
0	Add1	No						LD	F0	0	R1
0	Add2	No						MULTI	F4	F0	F2
0	Add3	No						SD	F4	0	R1
0	Mult1	Yes	MULTD		R(F2)	Load3		SUBI	R1	R1	#8
0	Mult2	No						BNEZ	R1	Loop	

Register result status

Clock	R1		F0	F2	F4	F6	F8	F10	F12	...	F30
18	56	Qi			Mult1						

Loop Example Cycle 19

Instruction status

Instruction	j	k	iteration	Issue	Execution complete	Write Result
LD F0	0	R1	1	1	9	10
MULTI F4	F0	F2	1	2	14	15
SD F4	0	R1	1	3	18	19
LD F0	0	R1	2	6	10	11
MULTI F4	F0	F2	2	7	15	16
SD F4	0	R1	2	8		

	Busy	Address	Qi
Load1	No		
Load2	No		
Load3	Yes	64	Qi
Store1	No		
Store2	Yes	72	M(72)*R(
Store3	Yes	64	Mult1

Reservation Stations

Time	Name	Busy	Op	S1 Vj	S2 Vk	RS for Qj	RS for Qk	Code:
0	Add1	No						LD F0 0 R1
0	Add2	No						MULTI F4 F0 F2
0	Add3	No						SD F4 0 R1
0	Mult1	Yes	MULTD		R(F2)	Load3		SUBI R1 R1 # 8
0	Mult2	No						BNEZ R1 Loop

Register result status

Clock	R1		F0	F2	F4	F6	F8	F10	F12 ...	F30
19	56	Qi			Mult1					

RHK.S96 49

Loop Example Cycle 20

Instruction status

Instruction	j	k	iteration	Issue	Execution complete	Write Result
LD F0	0	R1	1	1	9	10
MULTI F4	F0	F2	1	2	14	15
SD F4	0	R1	1	3	18	19
LD F0	0	R1	2	6	10	11
MULTI F4	F0	F2	2	7	15	16
SD F4	0	R1	2	8	20	

	Busy	Address	Qi
Load1	No		
Load2	No		
Load3	Yes	64	Qi
Store1	No		
Store2	Yes	72	M(72)*R(
Store3	Yes	64	Mult1

Reservation Stations

Time	Name	Busy	Op	S1 Vj	S2 Vk	RS for Qj	RS for Qk	Code:
0	Add1	No						LD F0 0 R1
0	Add2	No						MULTI F4 F0 F2
0	Add3	No						SD F4 0 R1
0	Mult1	Yes	MULTD		R(F2)	Load3		SUBI R1 R1 # 8
0	Mult2	No						BNEZ R1 Loop

Register result status

Clock	R1		F0	F2	F4	F6	F8	F10	F12 ...	F30
20	56	Qi			Mult1					

RHK.S96 50

Loop Example Cycle 21

Instruction status

Instruction	j	k	iteration	Issue	Execution complete	Write Result
LD F0	0	R1	1	1	9	10
MULTI F4	F0	F2	1	2	14	15
SD F4	0	R1	1	3	18	19
LD F0	0	R1	2	6	10	11
MULTI F4	F0	F2	2	7	15	16
SD F4	0	R1	2	8	20	21

	Busy	Address	Qi
Load1	No		
Load2	No		
Load3	Yes	64	Qi
Store1	No		
Store2	No		
Store3	Yes	64	Mult1

Reservation Stations

Time	Name	Busy	Op	S1 Vj	S2 Vk	RS for Qj	RS for Qk
0	Add1	No					
0	Add2	No					
0	Add3	No					
0	Mult1	Yes	MULTD		R(F2)	Load3	
0	Mult2	No					

Code:

```
LD    F0   0  R1
MULTI F4   F0 F2
SD    F4   0  R1
SUBI  R1   R1 # 8
BNEZ  R1   Loop
```

Register result status

Clock	R1		F0	F2	F4	F6	F8	F10	F12 ...	F30
21	56	Qi			Mult1					

Tomasulo Summary

- **Prevents Register as bottleneck**
- **Avoids WAR, WAW hazards of Scoreboard**
- **Allows loop unrolling in HW**
- **Not limited to basic blocks (provided branch prediction)**
- **Lasting Contributions**
  - **Dynamic scheduling**
  - **Register renaming**
  - **Load/store disambiguation**
- **Next: More branch prediction**